

#1-Open your RIP profile in Rampage

Prescan Prescan Rules RIP Trap Marks Output

Queues Page Info Tools Jobs

PDF Page Prescan

Stop After Prescan: No (Only on Error)

Generate PDF Report: On Error

PDF Report Format: Layer

Unembedded Font: Stop with Error

Exceptions...

Subset Fonts

Convert Fonts to Outlines

Embed Fonts Folder:

Recompress Images

Gray/Color Images: Retain Existing Format

Quality: Maximum

Bitmap Images: Retain Existing Format

Gray/Color Image Res.: Below dpi

Action: Report Error

Above dpi

Action: Report Error

Bitmap Image Res.: Below dpi

Action: Report Error

Above dpi

Action: Report Error

#2- enable Use Color Policy and choose Edit Policy

Use Color Policy

Edit Policy...

Transparency Blend Space: Set to CMYK

Object is Tagged with ICC: Do not check

Action: Report Error

Fill & Stroke Ink Coverage: Above %

Action: Report Error

Image Ink Coverage: Above %

Action: Report Error

Line Thickness: Below pt.

Action: Report Error

#3-The color space of the pdf you wish to convert*****Note-To be able to choose profiles they must reside in the ICC Profiles folder located in the Rampage folder

Color Policy

Action	Default Source Profile	Rendering Intent
RGB Images: Convert to Output Intent	sRGB_Color_Spa...	Relative Colorimetric
RGB Text and Graphic:		Relative Colorimetric
CMYK Images: <input checked="" type="checkbox"/> Convert to Output Intent	EuroscaleCoated...	Relative Colorimetric
CMYK Text and Graphic: <input checked="" type="checkbox"/> Convert to Output Intent		Relative Colorimetric
Grayscale Images: <input type="checkbox"/> Convert to Output Intent	Dot Gain 25 prct...	From PDF
Grayscale Text and Graphic: <input type="checkbox"/> Convert to Output Intent		From PDF
Output Intent: <input type="checkbox"/> From PDF if Present	G7_Coated_5_2011_MaxK.icc	

Discard Embedded Profiles

Black Point Compensation

Preserve Black Objects

OK

#4- Use Relative Colorimetric when converting CMYK-CMYK

#5-Select your profile with the desired TAC. *****To be able to choose profiles they must reside in the ICC Profiles folder located in the Rampage folder

#6-Enable BPC & Preserve Black Objects